

ASY-RWG Series Open-ended Rectangular Waveguide Probes

sales@asysol.com



- Open-ended Rectangular Waveguide Probes (RWG) are commonly used as near-field probes in planar near-field and cylindrical near-field antenna measurements. The probe design is based upon standard rectangular waveguides and consequently the probes can be manufactured for any standard frequency band from 500MHz up to 60GHz. The radiation characteristics of RWG can be well predicted by analytical formulas that facilitate a simplified probe pattern correction.
- ASYSOL RWGs are equipped with an integrated coaxial connector, absorber shield, and dedicated mechanical interface with a standardised mounting flange.
- All RWGs are supplied with a test report, including measurement results of the main characteristics:
 - Reflection coefficient
 - Sweep gain
 - Sweep on-axis cross-polarisation
 - Pattern at a series of frequencies across the band





| Model Number | WR | Frequency band [GHz] | Nominal gain [dBi] | VSWR | Cx-pol [dB] |
|--------------|------|-------------------------|-----------------------|---------|----------------|
| ASY-RWG-005 | 1500 | 0.5 – 0.75 | 6 | < 2.2:1 | < -40 |
| ASY-RWG-007 | 975 | 0.75 – 1.1 | 6 | < 2.2:1 | < -40 |
| ASY-RWG-011 | 650 | 1.1 – 1.7 | 6 | < 2.2:1 | < -40 |
| ASY-RWG-017 | 430 | 1.7 – 2.6 | 6 | < 2.2:1 | < -40 |
| ASY-RWG-026 | 284 | 2.6 - 3.9 | 6 | < 2.2:1 | < -40 |
| ASY-RWG-039 | 187 | 3.9 – 5.8 | 6 | < 2.2:1 | < -40 |
| ASY-RWG-058 | 137 | 5.8 - 8.2 | 6 | < 2.2:1 | < -40 |
| ASY-RWG-070 | 112 | 7.0 – 10.0 | 6 | < 2.2:1 | < -40 |
| ASY-RWG-082 | 90 | 8.2 – 12.4 | 6 | < 2.2:1 | < -40 |
| ASY-RWG-100 | 75 | 10.0 – 15.0 | 6 | < 2.2:1 | < -40 |
| ASY-RWG-124 | 62 | 12.4 – 18.0 | 6 | < 2.2:1 | < -40 |
| ASY-RWG-150 | 51 | 15.0 – 22.0 | 6 | < 2.2:1 | < -40 |
| ASY-RWG-180 | 42 | 18.0 – 26.5 | 6 | < 2.2:1 | < -40 |
| ASY-RWG-220 | 34 | 22.0 - 33.0 | 6 | < 2.2:1 | < -40 |
| ASY-RWG-265 | 28 | 26.5 - 40.0 | 6 | < 2.2:1 | < -40 |
| ASY-RWG-400 | 19 | 40.0 - 60.0 | 6 | < 2.2:1 | < -40 |



Simulated vs. measured gain over frequency



Simulated vs measured radiation pattern at 8.2GHz

Ver032018



Edificio Antalia. Albasanz 16. 28037 Madrid +34 91 567 97 00 | alavaingenieros.com | alava@grupoalava.com Madrid | Barcelona | Zaragoza | Lisboa | Lima | Quito | Texas Antenna Systems Solutions S.L. Albert Einstein 12 39011 Santander Cantabria, Spain 😞 sales@asysol.com

C +44 8700 555 010

@ www.asysol.com

